

## U21<sup>LED</sup>

indoor self-contained emergency lighting luminaires LED



6616 11



6616 07

Spare batteries selection chart **p. 661**  
 Technical characteristics **p. 653**  
 Adhesive labels **p. 660**

LED maintained and non maintained units  
 Certified to IEC and EN 60598-2-22 standards  
 High power LEDs  
 IP 42 - IK 04  
 Duration: 1 and 3 hours  
 Ni-Cd or Ni-MH batteries  
 Recharge time: 24 hours  
 Charge monitor with a green LED  
 Power supply: 230 V $\sim$   $\pm$  10% - 50/60 Hz  
 Class II  $\square$   
 High capacity screw terminals (2 x 2.5 mm<sup>2</sup>)  
 Flush-mounting in dry partitions (ceiling & wall): add flush-mounting frame Cat.No 6 617 20  
 Flush-mounting in masonry (brick or concrete wall): add both flush-mounting box Cat.No 0 617 21 and flush-mounting frame Cat.No 6 617 20  
 To be equipped with labels (p. 660)  
 Can be equipped with metallic protection grids Cat.Nos 0 626 90/92 (p. 660)

Pack	Cat.Nos	Standard luminaires
		Require normal lighting manual switching off in order to test emergency lighting
		<b>Non-maintained (NM)</b>
1	6 616 01	70 lm - 1h (LEDs)
1	6 616 02	100 lm - 1h (LEDs)
1	6 616 05	160 lm - 1h (LEDs)
		<b>N</b>
1	6 616 08	200 lm - 1h (LEDs)
1	6 616 09	350 lm - 1h (LEDs)
1	6 616 11	90 lm - 3h (LEDs)
		<b>Maintained / Non-maintained (M/NM)</b>
		Can also operate in Non maintained mode according to the wiring of normal lighting
1	6 616 03	100 lm - 1h (LEDs)
1	6 616 06	200 lm - 1h (LEDs)
1	6 616 07	350 lm - 1h (LEDs)
1	6 616 10	100 lm - 3h (LEDs)

Pack	Cat.Nos	Autotest & addressable Maintained / Non-maintained luminaires (M)
		Autotest/addressable luminaires incorporate an automatic self-testing system in order to check the emergency mode. Tests result is visible on 2 signalling LEDs (green-OK and yellow-defective) Addressable function is activated by setting an ID on each luminaire with configuration tool (Cat.No 0 626 10) and wiring a complementary BUS line. Operating state of all addressable luminaires can be centralized by the control interface (Cat.No 0 626 00) and monitored on a local touch screen controller (Cat.No 0 626 01), or with the building's plan on Legrand Vision System (LVS2) PC software (Cat.No 0 626 02). These Maintained luminaires can also operate in Non maintained mode according to the wiring of normal lighting
1	6 626 03	100 lm - 1h (LEDs)
1	6 626 06	200 lm - 1h (LEDs)
1	6 626 07	350 lm - 1h (LEDs)
1	6 626 10	100 lm - 3h (LEDs)

Pack	Cat.Nos	Accessories
10	6 617 20	Flush-mounting frame for dry partition
10	0 617 21	Flush-mounting box for masonry partition

To help you locate your emergency lighting units with DIALux lighting calculation software, you can download the Legrand plug-in for DIALux on [www.export.legrand.com/EN](http://www.export.legrand.com/EN)

## U21<sup>NEW</sup> - indoor self-contained emergency lighting luminaires

6 W fluorescent



6617 02

Spare batteries selection chart **p. 661**  
 Technical characteristics **p. 653**  
 Adhesive labels **p. 660**

6 W fluorescent non-maintained units  
 Certified to IEC and EN 60598-2-22 standards  
 IP 42 - IK 04  
 Power supply: 230 V $\sim$   $\pm$  10%  
 Plug-in base to ease fixing, cabling and connection  
 Transparent diffuser  
 Duration time: 1, 2 and 3 hours  
 Ni-Cd batteries  
 Recharge time: 24 hours  
 Green LED charge monitor  
 High capacity screw terminals (2 x 2.5 mm<sup>2</sup>)  
 Flush-mounting in dry partitions (ceiling): add flush-mounting frame Cat.No 6 617 20  
 Flush mounting in masonry (brick or concrete wall): add both flush-mounting box Cat.No 0 617 21 and flush-mounting frame Cat.No 6 617 20  
 To be equipped with labels (p. 660)  
 Can be equipped with metallic protection grids Cat.Nos 0 626 90/92 (p. 660)

Pack	Cat.Nos	Standard luminaires
		Standard luminaires require normal lighting manual switching off in order to test emergency lighting
		<b>Non-maintained 6 W fluorescent luminaires</b>
1	6 617 10	50 lm - 1h (1 x 6 W)
1	6 617 01	70 lm - 1h (1 x 6 W)
1	6 617 02	110 lm - 1h (1 x 6 W)
1	6 617 05	160 lm - 1h (1 x 6 W)
1	6 617 06	240 lm - 1h (1 x 6 W)
1	6 617 07	300 lm - 1h (1 x 6 W)
1	6 617 11	90 lm - 3h (1 x 6 W)
		<b>Accessories</b>
10	6 617 20	Flush mounting frame for dry partition
10	0 617 21	Flush mounting box for masonry partition

To help you locate your emergency lighting units with DIALux lighting calculation software, you can download the Legrand plug-in for DIALux on [www.export.legrand.com/EN](http://www.export.legrand.com/EN)